

Miniature Cylindrical MIL-C-26482, Series 2 contact arrangements

front face of pin insert or rear face of socket insert illustrated

Insert Arrangement	8-33	8-98	10-06	12-03	12-08	12-10
Service Rating	I	I	I	II	I	I
Number of Contacts	3	3	6	3	8	10
Contact Size	20	20	20	16	20	20


Insert Arrangement	14-04	14-05	14-09	14-12	14-15
Service Rating	I	II	I	I	I
Number of Contacts	4	5	5 4	8 4	14 1
Contact Size	12	16	20 12	20 16	20 18

Insert Arrangement	14-18	14-19	16-08	16-23	16-26
Service Rating	I	I	II	I	I
Number of Contacts	18	19	8	22 1	26
Contact Size	20	20	16	20 16	20


CONTACT LEGEND ○ ● ◐
 20 16 12

Miniature Cylindrical MIL-C-26482, Series 2 contact arrangements


front face of pin insert or rear face of socket insert illustrated




18-08



18-11



18-30



18-32


Insert Arrangement
Service Rating
Number of Contacts
Contact Size

I
8
12


II
11
16

I
29 1
20 16


I
32
20




20-16



20-24



20-39



20-41


Insert Arrangement
Service Rating
Number of Contacts
Contact Size

II
16
16


I
24
20

I
37 2
20 16


I
41
20



22-12



22-19



22-21

Insert Arrangement
Service Rating
Number of Contacts
Contact Size

I
12
12

I
19
12


II
21
16

CONTACT LEGEND




Miniature Cylindrical MIL-C-26482, Series 2 contact arrangements

front face of pin insert or rear face of socket insert illustrated




Insert Arrangement
Service Rating
Number of Contacts
Contact Size


22-32
I
32
20



22-41
I
27 14
20 16




22-55
I
55
20




Insert Arrangement
Service Rating
Number of Contacts
Contact Size


22-95
I
26 6
20 12



24-19
II
19
12



24-31
I
31
16



Insert Arrangement
Service Rating
Number of Contacts
Contact Size

24-61
I
61
20

CONTACT LEGEND

○ 20 ● 16 ◐ 12